


MISCO. Accessories

2 WATT, 25 VOLT LINE MATCHING TRANSFORMER

PART #: 2T25

Model 2T25 is a 2 watt line matching transformer for use in constant voltage sound reinforcement systems. This unit has an insertion loss that does not exceed 1.5 dB with a frequency response of +/- 3.2 dB from 100 - 15KHz. The primary taps are 2, 1, 0.5, and 0.25 watts. The secondary impedance is 8 ohms. Model 2T25 is designed for 25 volt lines. See detailed specifications below.

- 2 Watt
- 25 Volt
- 8 Secondary Impedance
- 4, 2, 1, 0.5, 0.25 Primary Taps
- +/- 3.2 dB from 100 - 15KHz Frequency Response



Primary Specifications

- 2 Watt
- 25 Volt
- 8 Secondary Impedance
- 4, 2, 1, 0.5, 0.25 Primary Taps
- +/- 3.2 dB from 100 - 15KHz Frequency Response