

The JC69CD is a classic full range, 8 ohm, 6 x 9" speaker made for line arrays, voice communications, electronic organs, and more. Increase your sound system's high frequency dispersion with this driver's whizzer cone attached directly to the voice coil.

- Full range speaker with whizzer
- 6 x 9" steel basket diameter
- 15 watts, 8 ohm, 92 dB SPL
- 1" copper voice coil, aluminum former
- Ferrite magnet, paper cone

For a 4 ohm impedance, see the [JC69CD-4](#).



Primary Specifications

| | |
|--------------------------------------|------------------|
| Size, Nominal (inch & mm) | 6" Oval (152 mm) |
| Rated Impedance (Ω) | 8 |
| Sensitivity (dB SPL) ¹ | 92 |
| Frequency Range (Hz) | 55 - 15, 000 |
| Resonant Frequency (Fs) (Hz) +/- 15% | 61 |

More Specifications

| | |
|---------------------------------|---------------------------|
| Application | Auto / Motorcycle, Indoor |
| RoHS Compliant | No |
| DC Resistance (Re) (Ω) | 6.8 |
| Program Power (W) | 30 |

Small Signal Parameters

| | |
|--------------------------------------|------|
| Nominal Impedance (Z) (Ω) | 8 |
| DC Resistance (Re) (Ω) | 6.8 |
| Resonant Frequency (Fs) (Hz) +/- 15% | 61 |
| Mechanical Q Factor (Qms) | 2.2 |
| Electrical Q Factor (Qes) | 0.71 |
| Total Q Factor (Qts) | 0.54 |

Material Descriptions

| | |
|----------------------------|-------------------------|
| Basket Type | Stamped steel |
| Terminal Size (mm) | 0.205 x 0.02 |
| Voice Coil Diameter (mm) | 25.4 |
| Voice Coil Wire Material | Copper |
| Voice Coil Former Material | Aluminum |
| Magnet Material | Ferrite |
| Magnet Weight (g) | 284 |
| Cone Body Material | Paper |
| Cone Surround Material | Pre-treated black cloth |
| Dust Cap Material | Paper |
| Net Weight (kg) | 0.96 |

